

KMG 7.1



1 x Remote

- 7 Input modes
- 6 Programmable Sound experience
- Volume Control , Mic Volume
- Sub Woofer Volume Control
- Center Speaker Volume Control
- Echo Effects Volume Control
- 138 x 45 x 16 mm
- 2 x AA Battery




2 x Wireless Microphone

- LCD Display , Battery Indicator/ Frequency Indicator
- Frequency: 740-790Mhz UHF
- Dynamic Range: 100dB
- THD (Total Harmonic Distortion) : <5% (1kHz, 1 W)
- Working Range: 50m (Without obstacles)
- Battery Life: 8 Hrs
- Battery: 2 x 1.5AA
- Frequency Learning VIA RF



7 x Starlet Satellite Speakers

- THD (Total Harmonic Distortion) : <5% (1kHz, 1 W)
- Power : 40W
- 7 Satellite Speakers
- 2x 2.5" Driver tweeter
- Sensitivity 88dB
- Frequency Response: 300Hz-20KHz
- High graded Polymer ABS Plastic, Aluminium Grill
- Matte Black Finish
- 61 x 83 x 123 mm | 0.5kg
- **Wall Mount Bracket | Floor Stand



1 x 10" Bass Module

- THD (Total Harmonic Distortion) : <5% (1kHz, 1 W)
- Maximum Power : 100W
- 1 x 10" Driver
- Sensitivity : 84dB
- Frequency Responds: 37-500Hz
- Side Ported Passive Woofer
- 328 x 363 x 340 mm | 12Kg
- ** Wall Bracket | Floor Mount

1 x Main Module

- 60W x 7 | 120W x 1 Woofer
- 3 x HDMI Input | 2.0 | HDCP 2.2 |
- 4K Pass-Thru (ARC)
- Bluetooth 4.2 (SBC and AAC decoder support)
- 1 x USB (Calibration) | 1 x RCA Input
- 1 x Coaxial | 1 x TOSLink
- 2 x 1/4" Mic Input
- 15band Parametric Equaliser for Music input,
- 15band Parametric Equaliser for Microphone (Individual) input.
- 15band Parametric Equaliser for Left/Right/ Center Speaker
- 15band Parametric Equaliser for Surround Left/Right Speaker
- 15band Parametric Equaliser for Surround Back Left/Right Speaker
- 5band Parametric EQ for Echo, Reverb.
- Precise Time delay for Reverb and Echo function
- 6band Parametric EQ for Woofer
- Individual Gain Control for 7 Input Source
- 430 x 268 x 86 mm | 4.5Kg



Package Size: 495 x 426 x 480 | 28kg | FCL20: 240 | FCL40: 500

Find out more setup information and Detailed information at www.thunderstone.technology



Mounting systems (Optional)

KMG-B1 is supplied in box. Other bracket accessories are optional items by Bose
KMG3.1 Basic wiring and installation \$380, KMG 7.1 Basic wiring and installation \$580



KMG-B2 \$15/pc
KMG-SS1 \$29/pc
KMG-LS1 \$59/pc